


5-WIRE SMATV TAP RANGE

Overview

Hills 2-way 5-Wire multi-taps are suitable and approved for use in FOXTEL PAY TV installations with SMATV applications.

Features & Benefits

- 2-way multi-taps.
- Application in 5-wire systems.
- DC pass / isolation between SAT inputs / outputs and taps.
- Sheet metal housing.
- Indoor wall mounting.
- Earthing terminal.
- FOXTEL approved.
- Coloured coded ports for easy identification



BC84487

PART #		BC84487	BC84488	BC84489
MANUFACTURER		SWITCH MASTER		
TAP VALUE		10dB	15dB	20dB
MODEL REF #		HI52WT10	HI52WT15	HI52WT20
FOXTEL Approval		F30843	F30844	F30845
TRUNK and TAP INPUTS		4 Satellite + 1 Terrestrial		
FREQUENCY	Satellite	950 – 2150MHz		
RANGE	Terrestrial	5 – 862MHz		
TAP or SIDE	Satellite	10dB MAX	15dB MAX	20dB MAX
LOSS	Terrestrial	10dB MAX	15dB MAX	20dB MAX
TRUNK or	Satellite	3.0dB MAX	3.0dB MAX	3.0dB MAX
THROUGH LOSS	Terrestrial	3.0dB MAX	3.0dB MAX	3.0dB MAX
MAX DC pass	TAP ports	1000mA – for 1H + 2H combined		
Current	TRUNK ports	2000mA – for 1H + 2H combined		
MAX DC pass	SWITCHABLE	INPUT to TRUNK output		
Current via: -	SWITCHABLE	INPUT to TAP output 1		
H1 + H2	SWITCHABLE	INPUT to TAP output 2		
Trunk and Tap connector type		F-TYPE FEMALE		
Dimensions (L x W x H)		160 x 138 x 50mm		

Listed part numbers and products subject to change without notice.

For more information on these and other best-in-class solutions from Hills call us on **1300 HILLS1 (445 571)** or visit **hills.com.au**



TRUSTED TECHNOLOGY